

## HCS-5100R/40F Digital Infrared Receiver



### Features

- Compliant with ISO 22259
- Compatible with any other IR simultaneous interpretation system compliant to IEC 61603-7
- Independent intellectual property chipset for digital infrared processor, and DQPSK digital modulation/demodulation technology
- Transmitting in 1~8 MHz frequency band eliminates disturbance from high frequency lighting systems
- Channel selection via up/down button, at most 40 channels available
- Back-lighting LCD display with channel number, language name, battery and signal status indication
- Number of available channels is always the same as the number of channels in use by the system, eliminating the need to scroll through unused channels
- Adjustable volume
- Unique 270° super wide reception angle, ensuring perfect sound quality even when casually placed
- Audio signal automatically muted when signal is too low, ensuring that the user receives only high quality audio
- Ergonomically compact and elegant design
- Lightweight and handy receiver in conjunction with headphone (HCS-5100PA) for easy and comfortable use
- Can be hung over the neck via a nice strap or fit into the shirt pocket
- Freedom of movement within the range of IR power radiator
- No limit to the receiver number within the IR power radiation range
- Works without errors, even in bright sunlight
- Built-in high precision rechargeable circuitry to prolong battery life
- Can be used with disposable batteries (2×AA alkaline batteries, not included) or environmentally-friendly Li-ion rechargeable battery pack (not included)
- No power consumption when headphone is disconnected
- Measurement mode for easy checking of radiator coverage
- Can work with HCS-5300/80 new generation digital infrared wireless conference system and achieve up to 1+7 channels infrared wireless simultaneous interpretation

HCS-5100R/40F is a infrared receiver with 40 language channels. Both rechargeable Li-ion battery and disposable battery can be used. The receiver is equipped with channel selector, volume control, power switch, Ø 3.5 mm stereo earphone jack, and charging circuit on the PCB. A LCD displays channel number with language name, received signal intensity, battery capacity and volume.

### Controls and Indicators

- LCD displays channel number, language name, battery capacity, signal intensity and volume
- Power switch
- Channel selector buttons
- Volume control buttons

### Interconnections

- Ø 3.5 mm stereo earphone jack
- Charging contacts

### Technical Specifications

#### System Specifications

Modulation.....	DQPSK
Modulation frequency.....	1 to 8 MHz
	Carriers 0 to 5; 2 to 6 MHz, according to IEC 61603-7
Frequency response.....	20 Hz to 10 kHz (-3 dB) at standard quality; 20 Hz to 20 kHz (-3 dB) at perfect quality
THD at 1 kHz.....	≤0.05%
Isolation.....	≥85 dB
Dynamic range.....	≥90 dB
Weighted SNR.....	≥85 dBA

#### Electrical

IR irradiance level.....	4 mW/m <sup>2</sup> per carrier
Angle of sensitivity.....	270°
Headphone output level at 3.0 V.....	450 mVrms (speech at maximum volume, 32 Ohm headphone)
Headphone output freq. range.....	20 Hz to 20 kHz
Headphone output impedance.....	32 Ohm to 2 kOhm
Max. SNR.....	≥85 dBA
Supply voltage.....	2.5 V to 4.2 V, nominal 3.0 V
Power consumption	
Normal (at 3.0 V).....	38 mA (32 Ohm headphone)
Headphone jack unplugged.....	0 mA
Battery life	
2×AA alkaline cells.....	55 hours
Rechargeable battery pack.....	42 hours

**Mechanical**

Dimensions h x w x d (mm)..... 155 x 46 x 24

**Weight**

Excl. batteries..... 70 g

Incl. HCS-5100BAT-Li..... 115 g

Color..... Black (PANTONE 419 C)

---

**Ordering Information**

HCS-5100R/40F..... 40 CHs Digital Infrared  
Receiver (LCD, language  
display, optional  
rechargeable battery pack  
or 2xAA alkaline cells, excl.  
battery, black)